



RESPIRATORY

qPCR PANEL HANDBOOK

For Research Use Only. Not intended for diagnostic use.

CAT NO: YSP-RPP-42B10

96 well plates

VERSION 3.0



YouSeq Ltd
8 Moorside Place
Moorside Road
Winchester
SO23 7FX
United Kingdom

+44 (0) 333 577 6697
hello@youseq.com

youseq.com



INTENDED USE

This Respiratory Panel offers an efficient and user-friendly solution for the qualitative detection of the pathogenic markers listed in the **Panel Targets** section of this document (see final pages). Due to the inclusion of RNA based targets, use of the panel must be preceded by a cDNA synthesis step. It is designed to be used by trained professionals in a suitable molecular biology laboratory.

YouSeq panels comprise a set of multiplex real-time qPCR assays utilising hydrolysis probe technology to identify target nucleic acids for various research purposes. The primer/probes are pre-dispensed into a qPCR plate to be used in conjunction with good quality nucleic acids extracted from a variety of sample types and include essential control assays to ensure dependable results.

CONTENTS

Component	Included
Primer/probe qPCR Plate	10 x 96-well plates
PCR plate seals (to be used to seal the plate for PCR amplification)	10 x cap seals

RECOMMENDED REAGENTS & MATERIALS

General laboratory equipment (pipettes, pipette tips, (micro)centrifuge tubes, vortex mixer, plate centrifuge etc.)

Total nucleic acid extraction kit

YouSeq cDNA Synthesis Reagent Pack: [YSP-cDNA-42B10](#)

TetraTM 2X qPCR MasterMix: [YS-qP-TMM-10](#)

qPCR Panel Reagents Pack (inc. Positive Control): [YSP-Rg-42B10](#)

qPCR instrument with channels to detect FAM, VIC/HEX, ROX & CY5.

SUPPLEMENTARY MATERIALS

The following documents are available on request, please contact our customer success team at support@youseq.com.

Document	Description
YSP-RPP-42B10 - Plate Layout Template	Plate Layout Template files, built specifically for the panel and available for a range of qPCR instruments, to simplify your qPCR software setup.
YouSeq qPCR Data Analysis Pipeline IFU	User guide for YouSeq's real-time qPCR automated data analysis solution.



YOUSEQ

BEST PRACTICE

Decontamination:

Before beginning laboratory work, thoroughly decontaminate any work surfaces and pipettes being used, to eliminate potential contamination.

General use and set-up:

All components should be fully defrosted with contents at the bottom of the plate wells before opening. To ensure contents are at the bottom, centrifuge or gently tap the plate. After use, reagents should be returned to the freezer.

After any reagents are resuspended or combined, the tube should be pulse vortexed to ensure it is mixed well.

It is advised to set up the plate and reaction mix on ice to minimise artefact formation, which may reduce sensitivity.

When preparing the qPCR reaction mix, it is recommended to incorporate an overage into the calculations to compensate for potential losses incurred during pipetting.

Set-up environments:

It is best practice to set up qPCR plates in two different environments - a clean (no template) lab and PCR (template) lab.

No Template Control(s) (NTC) and Positive Control(s) (PTC) for each multiplex on the plate should be included in every run. To reduce contamination, NTCs and samples can be set up and sealed in a clean lab before moving to the PCR lab.

BREAK-AWAY PLATES

The supplied plates and seals can be cut at any junction point between wells using a pair of scissors. This allows for smaller plates to be run at the user's discretion.

Considerations:

When cutting the qPCR plate, make sure each section retains visible orientation markers, such as column numbers or row letters. This ensures the wells in the remaining plate sections can be confidently identified after the cut.

The plate ID is typically located on only one side of the plate. If cutting separates the unused portion from the plate ID, re-label that unused section (using ink or adhesive labelling) before storing it. This helps maintain traceability.

Ink or adhesive labelling should only be applied to the exterior surface of the plate and only on sections being stored. Before using any labelled plate section in a future qPCR run, ensure all adhesive labels are removed to avoid interference with the instrument.

Only the included plate cap seals should be used to seal the plate for PCR amplification.



Figure 1: Example of a 96 well break-away plate before and after cutting. The cutting orientation shown may not be suitable for this specific panel. For guidance, refer to the Plate Layout section (pg. 4)



YOUSEQ

PLATE LAYOUT

Multiplex primer/probe mixes are pre-dispensed into the plates provided according to the layout shown in Figure 2. For full target details, please refer to the Panel Targets section of this document (see final pages).

	1	2	3	4	5	6	7	8	9	10	11	12
A	1	1	1	1	1	1	1	1	1	1	1	1
B	2	2	2	2	2	2	2	2	2	2	2	2
C	3	3	3	3	3	3	3	3	3	3	3	3
D	4	4	4	4	4	4	4	4	4	4	4	4
E	5	5	5	5	5	5	5	5	5	5	5	5
F	6	6	6	6	6	6	6	6	6	6	6	6
G	7	7	7	7	7	7	7	7	7	7	7	7
H	8	8	8	8	8	8	8	8	8	8	8	8

Figure 2: 96 well plate layout indicating the location of each unique multiplex primer/probe mix.

SAMPLE LAYOUT

Addition of processed samples, PTCs and NTCs will follow the layout in Figure 3.

	1	2	3	4	5	6	7	8	9	10	11	12
A	PTC 1	1	2	3	4	5	6	7	8	9	10	NTC 1
B	PTC 2	1	2	3	4	5	6	7	8	9	10	NTC 2
C	PTC 3	1	2	3	4	5	6	7	8	9	10	NTC 3
D	PTC 4	1	2	3	4	5	6	7	8	9	10	NTC 4
E	PTC 5	1	2	3	4	5	6	7	8	9	10	NTC 5
F	PTC 6	1	2	3	4	5	6	7	8	9	10	NTC 6
G	PTC 7	1	2	3	4	5	6	7	8	9	10	NTC 7
H	PTC 8	1	2	3	4	5	6	7	8	9	10	NTC 8

Figure 3: Example 96 well plate to indicate the final dispense of nucleic acid samples and control location.

Please note: The product is associated with a specific Plate Layout Template file for the qPCR instrument of choice. This file comes with samples and targets pre-arranged in their correct positions and is designed to be imported directly into the software of various qPCR instruments.

To request the panel-specific Plate Layout Template file, please contact support@youseq.com.

It is strongly recommended to use these template files, as manually setting up the plate or editing the template may disrupt the automation of YouSeq's qPCR Data Analysis Pipeline.



YOUSEQ

RECOMMENDED BENCH SIDE PROTOCOL

cDNA SYNTHESIS

Extracted nucleic acid samples must undergo a cDNA synthesis step ahead of qPCR reaction set-up.

If utilising the YouSeq cDNA Synthesis reagents, follow the instructions supplied in the product handbook.

qPCR REACTION SET-UP

1. Remove the plate from the pouch and briefly spin the plate in a plate centrifuge. This will ensure the primer/probe mix is at the bottom of the wells before removing the plate seal.

Please note: If the plates needs to be cut, please do so at this stage before removing the seal, returning the unused portion of the plate to the freezer.

2. In an appropriately sized (micro)centrifuge tube, combine the following reagents to create a reaction mix that will cover all required wells (e.g. **samples**, **NTCs** and **PTCs**).

Please note: Include an overage to account for volume loss during pipetting.

Component	Volume (for 1 well)
2X qPCR MasterMix	10 μ L
DNase/RNase Free Water	5 μ L
Reaction mix volume	15 μ L

3. Mix the combined reagents by briefly vortexing or inverting.

Please note: For best results reaction mixes should be prepared and kept on ice until the amplification protocol is ready to start.

4. Remove plate seal and dispense 15 μ L of the reaction mix into all required wells.

5. For each **NTC**, add 5 μ L of DNase/RNase Free water into required well(s).

6. For each **sample**, add 5 μ L of the corresponding cDNA synthesis reaction into required well(s).

Please note: It is best practice to seal the **NTC** and **sample** wells, using the supplied cap seals, before proceeding to the **PTC** steps.

7. For each **PTC**, add 5 μ L of the prepared panel-specific **PTC**, into required well(s).

Please note: The **PTC** is a contamination risk and should be handled in a designated PCR (template) laboratory. Prepare the **PTC** reagent following the instructions supplied in the product handbook.

8. Seal the plate using the supplied cap seals.

9. Briefly vortex the sealed plate, then spin in a plate centrifuge to ensure all reagents are fully resuspended and at the bottom of the wells before running.



YOUSEQ

RECOMMENDED qPCR AMPLIFICATION PROTOCOL

1. Open the relevant qPCR instrument software and import the provided Plate Layout Template into the software using the 'Import' option. This will load the layout for the panel into the software (e.g. Target & sample names).
2. Within the loaded Plate Layout Template replace the pre-allocated sample names (e.g. Sample 1, Sample 2, etc.) with the sample IDs prior to data analysis. This can be performed either before the run has commenced or after the run has completed.

Please note: Manual plate setup or editing the Channels, Targets or Controls within the Plate Layout Template will impact the automation of YouSeq's qPCR Data Analysis Pipeline.

4. Load the plate onto the qPCR instrument.

Temperature	Time	Number of Cycles
95°C	3 minutes	-
95°C	15 seconds	x 5
60°C	60 seconds	
95°C	15 seconds	x 35
60°C 	60 seconds	

 Collect fluorogenic data through FAM, VIC/HEX, ROX & CY5 channels during this step.

5. Start the run.

ANALYSIS OF RESULTS

For automated analysis, output run files can be uploaded to YouSeq's qPCR Data Analysis Pipeline if this is the preferred method. Access to a unique analysis environment will be provided by the YouSeq Customer Success team.

YouSeq's qPCR Data Analysis Pipeline will provide a summary of the result for all samples in a PDF or CSV output, depending on user preference. Further details can be found on how to use the pipeline in the YouSeq qPCR Data Analysis Pipeline IFU.

Some users may prefer to analyse their data manually or adapt the output to custom workflows. For those opting out of the automated pipeline, the high data volume from YouSeq panels can be challenging to manage. For assistance adapting the pipeline, troubleshooting issues, or exploring manual analysis options, the Customer Success Team can provide help with personalised guidance at support@youseq.com.



YOUSEQ

PRODUCT SPECIFICATIONS

Storage

Store at -20°C from arrival. The primer/probe qPCR plate shelf life is outlined as an expiry date on the box label.

Suitable input material

The primer/probe qPCR plate will work well with any source of good quality nucleic acid. Good quality is defined as nucleic acid with high integrity (not degraded). Poor quality input nucleic acid is a leading cause of test failure.

Commensal Organisms

Commensal organisms are present as part of a healthy human microbiome and are found on the skin and in the respiratory tract. Contamination of samples and primer/probe qPCR plate is therefore possible, often seen as re-occurring late amplification for any assay targeting a commensal organism.

Regulatory Status

This product has been developed for Research Use Only (RUO) and is not intended for diagnostic use. It should not be used for diagnosis of disease or infection unless specifically approved by the regulatory authorities in the country of use.

Quality Control

In accordance with the YouSeq Ltd ISO EN 13485-certified Quality Management System, each lot of YouSeq Respiratory Panel is tested against predetermined specifications to ensure consistent product quality. The primers/probes typically demonstrate $\geq 95\%$ in silico specificity to their intended targets and are periodically checked against newly available sequence information to maintain their detection profile.

Technical Assistance

For customer support, please contact:

e-mail: support@youseq.com

phone: +44 (0)333 577 6697

Trademarks and Disclaimers

YouSeq®, Tetra™, CY5™, ROX™, VIC™.

Registered names, trademarks, etc. used in this document, even if not specifically marked as such, are not to be considered unprotected by law.

Not available in all countries.

© 2025 YouSeq Ltd; all rights reserved.

Internal product identifier

V.8

JSU0178

PANEL TARGETS

MPX	Target	Abbreviation	Target Gene	Potential cross-reactivity	Channel
1	Chlamydia pneumoniae	C.pneum	MOMP gene		FAM
	Legionella pneumophila	L.pneum	type IV secretion protein (IcmB) gene	L.cardiaca, L.lytica	ROX
	Mycoplasma pneumoniae	Mp.pneum	internal transcribed spacer (ITS) region		VIC/HEX
	RNaseP Endogenous Control	Endo Ctrl	RNaseP gene		CYS
2	Human Parainfluenza Virus 1	HPIV1	N gene		FAM
	Human Parainfluenza Virus 2	HPIV2	M gene		ROX
	Human Parainfluenza Virus 3	HPIV3	Hemagglutinin-Neuraminidase (HN) gene		VIC/HEX
	Human Parainfluenza Virus 4	HPIV4	L gene		CYS
3	Human coronavirus 229E	HCoV229E	N gene		VIC/HEX
	Human coronavirus HKU1	HCoVHKU1	N gene		ROX
	Human coronavirus NL63	HCoVNL63	M-gene		CYS
	Human coronavirus OC43	HCoVOC43	HE gene		FAM
4	Human Rhinovirus	HRV	5' untranslated region (UTR)		VIC/HEX
	Haemophilus influenzae	Haem.Flu	rpoB gene		ROX
	Human bocavirus	HBoV	NP1 gene		FAM
	Human metapneumoviruses	HMPV	N gene		CYS
5	Influenza A	FluA	M1 gene		FAM
	Influenza B	FluB	NEP/NS1 gene		VIC/HEX
	Respiratory syncytial virus (RSV)	RSV	M gene		CYS
	COVID19 N Gene	Covid19	N gene		ROX
	COVID19 RdRp Gene	Covid19	RdRP Gene		ROX
6	Human Adenovirus	Adeno	Penton base (Virion Component III)		FAM
	Moraxella catarrhalis	M.catar	downstream of thrB gene		VIC/HEX
	Enterovirus D68	EVD68	5'NCR		CYS
	Pseudomonas aeruginosa	P.aerug	regA gene		ROX
7	Candida albicans	C.albic	RPRI gene		CYS
	Klebsiella pneumoniae	K.pneum	upstream of YciY family protein gene		FAM
	Staphylococcus aureus	S.aureus	femB gene	S.argenteus, S.roterodami, S.schweitzeri	ROX
	Streptococcus pyogenes	S.pyoge	rpoB gene	S.canis, S.parasuis, S.suis, S.mitis, S.gwangjuense, S.chosunense, S.lactarius, S.oriscaviae, S.pseudopneumoniae, S.shenyangsis, S.vulneris	VIC/HEX
8	Acinetobacter baumannii	A.bauma	hrpA gene	A.nosocomialis	ROX
	Bordetella parapertussis	B.parap	downstream of ssb gene		CYS
	Bordetella pertussis	B.pertu	downstream of GAF domain-containing protein gene		VIC/HEX
	Streptococcus pneumoniae	S.pneum	alpha-fucosidase gene	S.mitis, S.toyakuensis	FAM

*Most target genes are detected using an individual assay within the specified channel. Some targets are strategically chosen to be detected in the same channel or have multiple assays to cover all species etc; a positive signal may be from one or more of the target genes.

Potential Cross-Reactivity

Due to extreme homology, it is possible that some of the target sequences may be present and detected in other related species. These potential cross-reactivity scenarios have been outlined in the Panel Targets List found at the back of this handbook.